

我司部分无线网卡支持在国产操作系统安装使用，具体驱动的安装方法以 FAX300U（免驱版）网卡为例。可选择通过双击驱动文件安装或使用命令行安装。

（适用型号：FAX300U（免驱版） / FAX300UH（免驱版） / FAX900U（免驱版） / FAX900U H（免驱版））

方法一：双击驱动文件安装

国产统信操作系统（UOS）和国产麒麟操作系统（Kylin）均支持 deb 格式的安装包进行软件安装。

1、从迅捷官网下载对应的网卡驱动程序：

服务与支持 > 下载中心 > 下载详情

驱动名称	FAX300U(免驱版) V1.0 Linux系统驱动程序20250118
适用系统	Linux、国产UOS、麒麟V4/V10等系统
驱动大小	0.78MB
上传日期	2025/1/24 13:55:02
下载链接	立即下载
驱动简介	适用于FAX300U(免驱版) V1.0版本的Linux系统驱动程序。

2、解压驱动文件压缩包后，可直接双击驱动（.deb 结尾），并输入当前帐号的密码（系统 Root 权限的账号密码）进行安装。

注：如果双击安装不成功，建议按照方法二使用命令行安装。

方法二：使用命令行安装

1、从迅捷官网下载对应的网卡驱动程序；

服务与支持 > 下载中心 > 下载详情

驱动名称	FAX300U(免驱版) V1.0 Linux系统驱动程序20250118
适用系统	Linux、国产UOS、麒麟V4/V10等系统
驱动大小	0.78MB
上传日期	2025/1/24 13:55:02
下载链接	立即下载
驱动简介	适用于FAX300U(免驱版) V1.0版本的Linux系统驱动程序。

2、解压驱动文件压缩包，在驱动所在文件夹，空白处右键选择 “在终端打开” ；



3、检查系统是否安装了 build-essential 包，如果没有，需要进行安装。检查和安装命令分别如下：

检查命令：dpkg -s build-essential

安装命令：sudo apt-get update

sudo apt-get install build-essential

4、安装驱动命令：sudo dpkg -i aic8800drvpackage.deb, -i 后面的是驱动包名称，需要根据实际的名称进行修改。

5、等待打印最后出现 Install aic8800 wifi driver successful!!!!, 表示网卡驱动安装成功。

```
Install aic8800 wifi driver successful!!!!
```

6、安装完成驱动后，可以使用 ifconfig 确认网卡是否加载成功。如果有对应的网卡设备，说明加载成功，可以在 wifi 连接界面连接路由器。

```
al@al:~$ ifconfig
eth0: flags=4099<UP,BROADCAST,MULTICAST>  mtu 1500
    ether 52:54:00:12:34:56 txqueuelen 1000  (Ethernet)
    RX packets 0  bytes 0 (0.0 B)
    RX errors 0  dropped 0  overruns 0  frame 0
    TX packets 0  bytes 0 (0.0 B)
    TX errors 0  dropped 0 overruns 0  carrier 0  collisions 0
    device interrupt 16  memory 0xed100000-ed120000

lo: flags=73<UP,LOOPBACK,RUNNING>  mtu 65536
    inet 127.0.0.1  netmask 255.0.0.0
    inet6 ::1  prefixlen 128  scopeid 0x10<host>
    loop txqueuelen 1000  (Local Loopback)
    RX packets 3613  bytes 261406 (261.4 KB)
    RX errors 0  dropped 0  overruns 0  frame 0
    TX packets 3613  bytes 261406 (261.4 KB)
    TX errors 0  dropped 0 overruns 0  carrier 0  collisions 0

wlan0: flags=4099<UP,BROADCAST,MULTICAST>  mtu 1500
    ether 88:ee:77:2f:5e txqueuelen 1000  (Ethernet)
    RX packets 0  bytes 0 (0.0 B)
    RX errors 0  dropped 0  overruns 0  frame 0
    TX packets 0  bytes 0 (0.0 B)
    TX errors 0  dropped 0 overruns 0  carrier 0  collisions 0

wlan1: flags=4099<UP,BROADCAST,MULTICAST>  mtu 1500
    ether 88:ee:77:2f:5e txqueuelen 1000  (Ethernet)
    RX packets 0  bytes 0 (0.0 B)
    RX errors 0  dropped 0  overruns 0  frame 0
    TX packets 0  bytes 0 (0.0 B)
    TX errors 0  dropped 0 overruns 0  carrier 0  collisions 0
```